Vibration Meter and Method of Measuring a
Viscosity of a Fluid

5   FIELD OF THE INVENTION

This invention relates to a method of measuring a
viscosity of a fluid flowing through a pipe, and to a
vibration meter for carrying out this method.
10   Furthermore, the invention relates to the use of a
flexural mode Coriolis mass flowmeter-densimeter for
measuring the viscosity of the fluid.

15   BACKGROUND OF THE INVENTION

Coriolis mass flowmeter-densimeters are preferably used
for measuring a mass flow rate and/or a density of a
fluid flowing through a pipe with a high degree of
20   accuracy.

A flexural mode Coriolis mass flowmeter-densimeter, as is
well known, is a vibration meter that has at least one
fluid-conducting flow tube which is inserted into a pipe
25   in a fluid-tight manner, particularly in a pressure-tight
manner, and which during operation oscillates
multimodally, particularly bimodally, about a position of
rest at at least one frequency. By means of an
electromechanical excitation arrangement, the flow tube
30   is commonly excited in a first, flexural mode of
vibration such that Coriolis forces are produced in the
moving fluid. In the case of a straight flow tube, the
first, flexural mode may, for instance, be a fundamental
mode of an elastic beam clamped at both ends, which, as
35   is well known, has a single antinode. In the case of a
bent flow tube, particularly a U- or Ω-shaped tube, a

fundamental mode of a beam clamped at one end is usually
excited as the first, flexural mode.

In such vibration meters, the Coriolis forces caused in
5   the moving fluid by the first, flexural mode
simultaneously excite a second vibration mode, whose
amplitude is also dependent on mass flow rate.

To determine the mass flow rate, a vibration of the flow
10   tube at an inlet end and a vibration of the flow tube at
an outlet end are sensed by means of a suitable sensor
arrangement and converted into a first sensor signal,
representing the inlet-side vibrations, and a second
sensor signal, representing the outlet-side vibrations.
15

Since the second vibration mode, here also a flexural
mode, is superimposed on the first flexural mode, the two
vibrations differ in phase. In Coriolis mass flowmeter-
densimeters, this phase difference, which is also
20   measurable between the two sensor signals in a
corresponding manner, serves as a measurand
representative of mass flow rate.

In Coriolis mass flowmeter-densimeters, a resonance
25   frequency and/or the amplitude of the first, flexural
mode are generally measurably dependent on the density of
the fluid. Thus, if the flow tube is constantly excited
at the resonance frequency of the first, flexural mode,
for example, this resonance frequency is a measure of the
30   instantaneous density of the fluid.

Vibration meters of the kind described, particularly
Coriolis mass flowmeter-densimeters, have been known for
a long time. For example, U.S. Patents 4,187,721,
35   4,801,897, 4,876,879, 5,301,557, 5,357,811, 5,557,973
5,648,616, 5,687,100, 5,796,011, and 6,006,609 as well as

European Patent 866 319 each disclose a vibration meter
for measuring a mass flow rate and a density of a fluid
flowing through a pipe, which vibration meter comprises:
- a transducer assembly

5   -- with at least one flow tube inserted into the pipe,

     --- which is clamped at an inlet end and an outlet end
         so as to be capable of vibratory motion, and

     --- which in operation oscillates relative to a position
         of rest at an adjustable excitation frequency,

10   -- with an electromechanical excitation arrangement for
        simultaneously producing spatial deflections and
        elastic deformations of the flow tube, and

     -- with a sensor arrangement, responsive to lateral
        deflections of the flow tube,

15   --- for generating a first sensor signal, representative
         of an inlet-side deflection of the flow tube, and

     --- for generating a second sensor signal,
         representative of an outlet-side deflection of the
         flow tube; and

20   - meter electronics

     -- with an excitation circuit which generates an
        excitation current for feeding the excitation
        arrangement, and

     -- with an evaluating circuit which derives from the

25   first and second sensor signals a mass flow rate
        value representative of the mass flow rate of the
        fluid and a density value representative of the
        density of the fluid.

30   Another physical parameter that is important for
     describing a moving fluid is viscosity. One can
     distinguish between kinematic viscosity and dynamic
     viscosity.

35   Viscometers and density-measuring vibration meters for
     moving fluids are also known in the art. U.S. Patent

4,524,610, for example, discloses a vibration meter for
measuring a viscosity of a fluid flowing through a pipe,
which vibration meter comprises:
- a transducer assembly

5   -- with a straight flow tube inserted into the pipe
           which
        --- has a lumen conducting the fluid and
        --- is clamped at an inlet end and an outlet end so as
           to be capable of vibratory motion,

10   -- with an electromechanical excitation arrangement for
           producing lateral deflections and/or torsional
           vibrations of the flow tube, and
        -- with a sensor arrangement, responsive to torsional
           vibrations of the flow tube, for generating a sensor

15   signal representative of central torsions of the flow
           tube; and
- meter electronics
        -- with an excitation circuit which generates an
           excitation current feeding the excitation

20   arrangement, and
        -- with an evaluating circuit
        --- which derives from the sensor signal and the
           excitation current a viscosity value representative
           of the viscosity of the fluid.

25

In this vibration meter serving as a viscometer-
densimeter, the flow tube oscillates either alternately
in the above-mentioned first, flexural mode for
determining density or in a torsional mode for

30   determining viscosity, or in both modes simultaneously,
but at different frequencies. The torsional vibrations
performed by the flow tube cause shearing forces in the
fluid, which, in turn, have a damping effect on the
torsional vibrations.

35

WO-A 95/16897 discloses a radial mode vibration meter
serving as a Coriolis mass flowmeter-densimeter-
viscometer for measuring a viscosity of a fluid flowing
through a pipe, which vibration meter comprises:
5   - a transducer assembly
         -- with a straight flow tube inserted into the pipe,
             which flow tube
         --- has a lumen conducting the fluid and
         --- is clamped at an inlet end and an outlet end so as
10   to be capable of vibratory motion,
         -- with an electromechanical excitation arrangement for
             producing axisymmetric deformations and/or lateral
             deflections of the flow tube, and
         -- with a sensor arrangement, responsive to axisymmetric
15   deformations of the flow tube, for producing a sensor
             signal representative of the deformations of the flow
             tube; and
         - meter electronics
         -- with an excitation circuit which generates an
20   excitation current feeding the excitation
             arrangement, and
         -- with an evaluating circuit
         --- which derives from the sensor signal and the
             excitation current a viscosity value representative
25   of the viscosity of the fluid.

In this Coriolis mass flowmeter-densimeter-viscometer,
the flow tube for determining viscosity and mass flow
rate oscillates primarily in an axisymmetric radial mode,
30   i.e., in a mode in which the wall of the flow tube is
elastically deformed in such a way that an axis of
gravity of the flow tube remains essentially in a static
position of rest. In addition, the flow tube is exited,
at least temporarily, in a secondary mode for instance in
35   the before mentioned first, flexural mode, which serves
to determine the density and pressure of the fluid.

While WO-A 95/16897 describes that radial mode vibration
meters can be used to measure both the mass flow rate and
the viscosity of fluids, the use of such vibration meters
for mass flow rate measurements has so far been limited
nearly exclusively to gaseous fluids. It has turned out
that the damping effect of viscosity, particularly on the
amplitude of the above-mentioned, preferably mass-flow-
rate-dependent second vibration mode, is so high that
even at viscosities that are just slightly above that of
water, this second vibration mode is practically no
longer detectable with sensors.

U.S. Patent 5,359,881 discloses a method of measuring the
viscosity of a moving fluid which uses a flexural mode
Coriolis mass flowmeter-densimeter to determine mass flow
rate and in which a pressure difference in the moving
fluid along the direction of flow is additionally sensed
to determine the viscosity of the fluid.

Furthermore, U.S. Patents 5,253,533 and 6,006,609
disclose flexural mode Coriolis mass flow/density sensors
which, in addition to sensing mass flow rate and/or
density, are suited for determining the viscosity of a
fluid. These Coriolis mass flow/density sensors each have
a straight flow tube which in operation oscillates,
simultaneously with a first, flexural mode, in a
torsional mode and thereby performs, at least in
sections, torsional vibrations about a longitudinal axis
of the flow tube.

It has turned out that the viscosities hitherto
determined in such Coriolis mass flow meters by measuring
solely the excitation current practically only for the
purpose of compensating the primary measured values,
namely a mass flow rate value and a density value, are

too inaccurate to be suitable for output as additional
viscosity values.

SUMMARY OF THE INVENTION

It is therefore an object of the invention to provide a
vibration meter for accurately measuring a viscosity of a
fluid flowing through a pipe which is also suited for
measuring, particularly simultaneously, a mass flow rate
and a density of the fluid. The invention further
provides a method which serves to increase the accuracy
of viscosity measurements by means of Coriolis mass
flowmeter-densimeters.

To attain the object, the invention provides a vibration
meter for measuring a viscosity of a fluid flowing
through a pipe, which vibration meter comprises:
- a transducer assembly
-- with at least one flow tube inserted into the pipe
   which
--- has a lumen conducting the fluid and
--- is clamped at an inlet end and an outlet end so as
    to be capable of vibratory motion,
-- with an electromechanical excitation arrangement for
   producing spatial deflections of the flow tube, and
-- with a sensor arrangement, responsive to lateral
   deflections of the flow tube,
--- for generating a first sensor signal, representative
    of an inlet-side deflection of the flow tube, and
--- for generating a second sensor signal,
    representative of an outlet-side deflection of the
    flow tube,
- the flow tube oscillating in operation relative to a
  position of rest at an adjustable excitation frequency
  to produce viscous friction in the fluid; and

- meter electronics
-- with an excitation circuit which generates an
   excitation current feeding the excitation
   arrangement, and
5 -- with an evaluating circuit
--- which derives from the first sensor signal and/or
   the second sensor signal and from the excitation
   current a viscosity value representative of the
   viscosity of the fluid.
10

The invention also provides a method of measuring a
viscosity of a fluid flowing through a pipe using a
vibration meter comprising:
- a transducer assembly
15 -- with at least one flow tube inserted into the pipe
   which in operation oscillates relative to a position
   of rest at an adjustable excitation frequency,
-- with an electromechanical excitation arrangement for
   producing spatial deflections of the flow tube, and
20 -- with a sensor arrangement, responsive to lateral
   deflections of the flow tube, for sensing an inlet-
   side and an outlet-side deflection of the flow tube;
   and
- meter electronics with
25 -- an excitation circuit which generates an excitation
   current feeding the excitation arrangement, and
-- an evaluating circuit,
- the vibration meter providing a density value,
   representative of a density of the fluid, and an
30   excitation frequency value, representative of the
   excitation frequency,
said method comprising the steps of:
- generating vibrations of the flow tube at the
   excitation frequency to produce viscous friction in
35   the fluid;

- sensing the excitation current feeding the excitation arrangement to generate a friction value representative of the viscous friction;
- sensing an inlet-side and/or an outlet-side deflection of the flow tube to generate an estimate representative of a velocity of a motion of the fluid, which causes the viscous friction;
- dividing the friction value by the estimate to obtain a quotient value representative of a damping of the oscillating flow tube caused by the viscous friction;
- deriving from the density value and the excitation frequency value a correction value dependent on the density of the fluid and on the excitation frequency; and
- deriving from the quotient value and the correction value a viscosity value representative of the viscosity of the fluid.

In a first preferred embodiment of the vibration meter of the invention, the evaluating circuit generates from the first sensor signal and/or the second sensor signal an estimate of a velocity of a motion of the fluid, which causes viscous friction.

In a second preferred embodiment of the vibration meter of the invention, the evaluating circuit derives from the excitation current a friction value representative of the viscous friction in the fluid.

In a third preferred embodiment of the vibration meter of the invention, the evaluating circuit derives from the friction value and the estimate a quotient value representative of a damping of the oscillating flow tube caused by the viscous friction.

In a fourth preferred embodiment of the vibration meter of the invention, elastic deformations of the lumen of the flow tube are caused by the spatial deflections of the flow tube.

5

In a fifth preferred embodiment of the vibration meter of the invention, torsions are caused in the flow tube about a longitudinal axis by the spatial deflections of the flow tube.

10

In a sixth preferred embodiment of the invention, the vibration meter delivers a mass flow rate value representative of an instantaneous mass flow rate of the fluid.

15

In a seventh preferred embodiment of the invention, the vibration meter delivers a density value representative of an instantaneous density of the fluid.

20   In a first preferred embodiment of the method of the invention, the viscosity value is obtained by dividing the quotient value by the correction value.

In a second preferred embodiment of the method of the
25   invention, the viscosity value is obtained by squaring the quotient value.

An aspekt of the invention is to derive the viscosity from the measured excitation current and from a lateral
30   deflection of the flow tube which is continuously sensed during operation of vibration meters of the kind described, particularly of Coriolis mass flowmeter- densimeters, preferably from the vibrations sensed at the inlet end and/or outlet end to measure mass flow rate.

35

One advantage of the invention is that it can be
implemented using conventional flexural mode Coriolis
mass flow/density sensors of the kind described without
having to make any changes to the mechanical design of
5   such sensors. Thus, the method of the invention can also
be implemented in Coriolis mass flowmeter-densimeters
that are already in use.

10   BRIEF DESCRIPTION OF THE DRAWINGS

The invention and further advantages will become more
apparent by reference to the following description of
embodiments taken in conjunction with the accompanying
15   drawings, in which:

      Fig. 1   shows schematically a vibration meter for a
                    moving fluid;

20   Fig. 2   is a first perspective view of an embodiment of
                    a transducer assembly of the vibration meter of
                    Fig. 1;

      Fig. 3   is a second perspective view of the transducer
25   assembly of Fig. 2;

      Fig. 4   is a perspective view of an enlarged portion of
                    the transducer assembly of Fig. 2;

30   Fig. 5   is a schematic block diagram of an evaluating
                    circuit of a vibration meter as shown in Fig.
                    1; and

      Figs. 6   are schematic block diagrams of embodiments of
35   to 9   the evaluating circuit of Fig. 5.

DETAILED DESCRIPTION OF EXEMPLARY EMBODIMENTS

5   While the invention is susceptible to various
        modifications and alternative forms, exemplary
        embodiments thereof have been shown by way of example in
        the drawings and will herein be described in detail. It
        should be understood, however, that there is no intent to
        limit the invention to the the particular forms diclosed,
10   but on the contrary, the intention is to cover all
        modifications, equivalents, and alternatives falling
        within the spirit and scope of the invention as defined
        by the intended claims.

15   Fig. 1 shows schematically a vibration meter that serves
        to sense a viscosity η of a fluid flowing through a pipe
        (not shown) and to map it into a viscosity value X_η
        representative of the viscosity η of the fluid.

20   Furthermore, the vibration meter, besides determining the
        viscosity η, preferably serves to determine a density ρ
        and a mass flow rate m of the fluid, particularly
        simultaneously, and to convert them in a corresponding
        manner into a density value X_ρ, representing the density
25   ρ, and a mass flow rate value X_m, representing the mass
        flow rate m.

        To accomplish this, the vibration meter is preferably
        designed as a Coriolis mass flowmeter-densimeter. The
30   construction and use of such Coriolis mass flowmeter-
        densimeters for measuring the mass flow rate m and/or the
        density ρ are described, for example, in the above-
        mentioned U.S. Patents 4,187,721, 4,876,879, 5,648,616,
        5,687,100, and 5,796,011 as well as in

European Patent 866 319, the disclosers of which are
hereby incorporated by reference.

To sense the above-mentioned parameters describing the
fluid, namely the viscosity η, the density ρ, and the
mass flow rate m, the vibration meter comprises a
transducer assembly 10, which is inserted into the pipe
in a fluid-tight manner, particularly in a pressure-tight
manner.

The vibration meter further comprises meter electronics
50 for controlling transducer assembly 10 and for
generating the aforementioned measured values. If the
vibration meter is designed to be coupled to a field bus,
particularly to a serial field bus, meter electronics 50
will include a suitable communication interface for data
communication, e.g., for the transmission of the measured
values to a higher-level stored-program control or a
higher-level process control system. Meter electronics 50
may, of course, be housed in a suitable electronics case
(not shown) in the manner familiar to those skilled in
the art.

Figs. 2 and 3 show an embodiment of a physical-to-
electrical converter arrangement serving as transducer
assembly 10. For example, the design of such a transducer
assembly is also described in detail in U.S. Patent
6,006,609, the disclosers of which are hereby
incorporated by reference. Such a transducer assembly is
used, for example, in Coriolis mass flowmeter-densimeters
of the "PROMASS I" series, which are manufactured by the
applicant.

Transducer assembly 10 comprises a straight flow tube 13,
which has an inlet end 11, an outlet end 12, a
predeterminable, elastically deformable lumen 13A, and a

predeterminable nominal diameter, as well as a rigid support frame 14, which is enclosed by a housing 100 and in which flow tube 13 is clamped so as to be capable of vibratory motion. "Elastic deformation" of lumen 13A as used herein means that in order to produce reaction forces describing the fluid, namely Coriolis forces, mass inertial forces, and/or shearing forces, during operation of transducer assembly 10, a three-dimensional shape and/or a spatial position of the fluid-conducting lumen 13A are changed in a predeterminable cyclic manner, particularly periodically, within an elasticity range of flow tube 13, cf., for example, U.S. Patents 4,801,897, 5,648,616, 5,796,011, and/or 6,006,609, the disclosers of which are hereby incorporated by reference. Materials especially suited for flow tube 13 are titanium alloys, for example. It is also possible to use other materials commonly employed for such flow tubes, particularly for bent tubes, such as stainless steel or zirconium.

Support frame 14 is fixed at inlet end 11 to an inlet plate 213 surrounding flow tube 13, and at outlet end 12 to an outlet plate 223 surrounding flow tube 13. Support frame 14 has a first support plate 24 and a second support plate 34, which are fixed to inlet plate 213 and outlet plate 223 in such a way as to be disposed in essentially parallel relationship to flow tube 13 and in spaced relationship from the latter and from each other, see Fig. 2. Thus, facing side surfaces of the two support plates 24, 34 are also parallel to each other.

Secured to flow tube 13 in spaced relation from support plates 24, 34 is a longitudinal bar 25, which serves as a balancing mass for absorbing vibrations of flow tube 13. As shown in Fig. 3, longitudinal bar 25 extends virtually parallel to the entire oscillable length of flow tube 13.

This, however, is not mandatory; longitudinal bar 25 may, of course, be shorter if necessary.

5   Support frame 14 with the two support plates 24, 34, inlet plate 213, outlet plate 223, and, optionally, longitudinal bar 25 thus has a longitudinal axis of gravity which is parallel to a longitudinal axis 13B of flow tube 13.

10   In Figs. 2 and 3, it is indicated by the heads of the screws shown that the above-mentioned fixing of support plates 24, 34 to inlet plate 213 and outlet plate 223 and to longitudinal bar 25 may be done by screwing; it is also possible to use other suitable forms of fastening

15   familiar to those skilled in the art.

As shown in Fig. 2, transducer assembly 10 further comprises an electromechanical excitation arrangement 16, which serves to spatially deflect flow tube 13 from a

20   static position of rest during operation, and thus to elastically deform the flow tube in a predeterminable manner.

To accomplish this, excitation arrangement 16, as shown

25   in Fig. 4, has a rigid lever arrangement 15, here a T-shaped arrangement, with a cantilever 154 and a yoke 163, the cantilever being rigidly fixed to flow tube 13. Yoke 163 is rigidly fixed to an end of cantilever 154 remote from flow tube 13, such that it is transverse to

30   longitudinal axis 13B of flow tube 13. Cantilever 154 may, for instance, be a metal disk which receives the flow tube in a bore. For further suitable implementations of lever arrangement 15, reference is made to the above-mentioned U.S. Patent 6,006,609.

35

Lever arrangement 15, as is readily apparent from Fig. 2,
is preferably arranged to act on flow tube 13
approximately midway between inlet end 11 and outlet end
12, so that in operation, flow tube 13 will exhibit a
5   maximum lateral deflection at a centric point.

To drive the lever arrangement 15, excitation arrangement
16, as shown in Fig. 4, comprises a first excitation coil
26 and an associated first permanent magnet 27 as well as
10   a second excitation coil 36 and an associated second
permanent magnet 37, which two excitation coils 26, 36
are joined, preferably nonpermanently, to support frame
14 below yoke 163 on both sides of flow tube 13. The two
excitation coils 26, 36 are preferably connected in
15   series; if necessary, they may, of course, be connected
in parallel.

As shown in Figs. 2 and 4, the two permanent magnets 27,
37 are fixed to yoke 163 at such a distance from each
20   other that during operation of transducer assembly 10,
permanent magnets 27 and 26 will be permeated essentially
by magnetic fields of excitation coils 26 and 36,
respectively, and moved by corresponding electromagnetic
forces. To this end, excitation arrangement 16 is fed by
25   a likewise oscillating, unipolar or bipolar excitation
current i_{exc} of adjustable amplitude and adjustable
frequency f_{exc} from a suitable excitation circuit 50A of
meter electronics 50, such that in operation, excitation
coils 26, 36 are traversed by this current, so that the
30   magnetic fields for moving permanent magnets 27, 37 are
produced. Excitation current i_{exc} may, for example, be a
harmonic, a triangular wave, or a square wave. The,
preferably single, frequency f_{exc} of excitation current
i_{exc}, as is customary in vibration meters of the kind
35   described, corresponds to an instantaneous mechanical
resonance frequency of the fluid-carrying flow tube 13.

The motions of permanent magnets 27, 37 produced by the
magnetic fields of excitation coils 26, 36 are
transmitted via yoke 163 and cantilever 154 to flow tube
5   13. These motions of permanent magnets 27, 37 are such
that yoke 163 is deflected from its position of rest at
the excitation frequency f_{exc}, alternately in the
direction of support plate 24 and in the direction of
support plate 34. A corresponding axis of rotation of
10   lever arrangement 15, which is parallel to the above-
mentioned longitudinal axis 13B of flow tube 13, may pass
through cantilever 154, for example.

Preferably, support frame 14 further comprises a holder
15   29 for electromagnetic excitation arrangement 16. This
holder 29 is connected, preferably nonpermanently, with
support plates 24, 34, and serves in particular to hold
excitation coils 26, 36 and individual components of the
below-mentioned magnetic-bearing arrangement 217.

20

As mentioned, excitation arrangement 16 serves to excite
flow tube 13 into mechanical vibration about a static
position of rest, whereby the tube performs at least
lateral deflections, particularly laterally oscillating
25   deflections.

In the transducer assembly 10 of the embodiment, these
lateral deflections simultaneously cause an elastic
deformation of the lumen 13A of flow tube 13, which is
30   firmly clamped at inlet end 11 and outlet end 12 in the
manner described above. This deformation of the lumen 13A
of flow tube 13 extends over virtually the entire length
of flow tube 13.

35   Furthermore, due to the clamping of flow tube 13 and to a
torque acting on flow tube 13 via lever arrangement 15,

torsion is induced in flow tube 13, at least in sections
thereof, simultaneously with the lateral deflection. This
torsion of flow tube 13 may be such that the direction of
a lateral deflection of the end of the cantilever remote

5   from flow tube 13 is either the same as or opposite to
that of the lateral deflection of flow tube 13. In other
words, flow tube 13 can perform torsional vibrations in a
first torsional mode, corresponding to the former case,
or in a second torsional mode, corresponding to the

10   latter case. In the transducer assembly 10 of the
embodiment, a natural frequency of the second torsional
mode, e.g., 900 Hz, is approximately twice as high as
that of the first torsional mode.

15   If flow tube 13 is to perform torsional vibrations only
in the second torsional mode, excitation arrangement 16
will advantageously incorporate a magnetic-bearing
arrangement 217 based on the eddy-current principle,
which serves to adjust and/or stabilize the position of

20   the axis of rotation, which depends particularly on the
instantaneous density of the fluid. With the magnetic-
bearing arrangement 217 it can thus be ensured that flow
tube 13 always vibrates in the second torsional mode, so
that any external interfering effects on flow tube 13

25   will not result in a spontaneous change to another
torsional mode, particularly to the first torsional mode.
Details of such a magnetic-bearing arrangement are
described, for example, in U.S. Patent 6,006,609; the use
of such magnetic-bearing arrangements is also known from

30   transducers of the aforementioned "PROMASS I" series.

For the transducer assembly 10 of the embodiment, the
excitation frequency f_{exc} will preferably be adjusted so
that exclusively the second torsional mode will be

35   excited and, accordingly, the first torsional mode will

be substantially suppressed; if necessary, however, the
first torsional mode may be excited.

5   As shown in Fig. 1, transducer assembly 10 further
comprises a sensor arrangement 60, which serves to sense
instantaneous spatial deflections of flow tube 13 and
generate corresponding signals, particularly analog
signals. To accomplish this, sensor arrangement 60
comprises a first sensor 17, which is responsive to
10   inlet-side, first laterally oscillating deflections of
flow tube 13, and a second sensor 18, which is responsive
to outlet-side, second laterally oscillating deflections
of flow tube 13. As shown in Fig. 2, the two sensors 17,
18 are positioned along flow tube 13 at a given distance
15   from each other, particularly at the same distance from
the midpoint of flow tube 13, by being fixed to support
frame 14, particularly to one of support plates 24, 34.

For sensors 17, 18, velocity-measuring electrodynamic
20   sensors are preferably used. It is also possible to use
displacement- or acceleration-measuring electrodynamic or
optical sensors, or other sensors familiar to those
skilled in the art that are responsive to such
deflections.
25

Thus, in operation, the two sensors 17, 18 of sensor
arrangement 60 generate a first sensor signal x_{s1},
representative of the inlet-side lateral deflections, and
a second sensor signal x_{s2}, representative of the outlet-
30   side lateral deflections.

As shown in Fig. 1, sensor signals x_{s1}, x_{s2} are applied to
a preferably programmable evaluating circuit 50B of meter
electronics 50, which serves to generate the viscosity
35   value X_η and the density value X_ρ. In a preferred

embodiment of the invention, evaluating circuit 50B
further provides the mass flow rate value X_m.

Each of the two sensor signals x_{s1}, x_{s2} has a frequency
5   corresponding to excitation frequency f_{exc}.

Preferably, sensor arrangement 60 further comprises an
amplifier circuit for adjusting the two sensor signals
x_{s1}, x_{s2} to the same amplitude. Amplitude control circuits
10   suitable for this purpose are shown in U.S. Patent
5,648,616 or European Patent 866 319, for example.

The excitation frequency f_{exc} is preferably adjusted using
a phase-locked loop of excitation circuit 50A, as is
15   usual in such excitation arrangements. For example, the
design and use of such a phase-locked loop for adjusting
a mechanical resonance frequency are described in detail
in U.S. Patent 4,801,897, the disclosers of which are
hereby incorporated by reference. It is also possible to
20   use other frequency control circuits familiar to those
skilled in the art which serve to adjust mechanical
resonance frequencies for vibration meters of the kind
described, cf., for example, U.S. Patents 4,524,610 and
4,801,897. Regarding the use of such a frequency control
25   circuit for transducers of the kind described, reference
is made to the "PROMASS I" series mentioned above.

To adjust the excitation current i_{exc}, use is made of an
amplifier circuit as is commonly employed in such
30   vibration meters, which is controlled by a frequency
control signal representative of the excitation frequency
to be adjusted, f_{exc}, and by an excitation current control
signal representative of the amplitude of the excitation
current to be adjusted, i_{exc}. The frequency control signal
35   may, for example, be a DC voltage delivered by the above-

mentioned frequency control circuit and having an
amplitude representative of the excitation frequency f_{exc}.

To generate the excitation current i_{exc}, excitation
circuit 50A comprises a suitable amplitude control
circuit which serves to derive the excitation current
control signal from the instantaneous amplitude of at
least one of the two sensor signals x_{s1}, x_{s2}, and from a
corresponding constant or variable amplitude reference
value W_1; if necessary, recourse can also be had to an
instantaneous amplitude of the excitation current i_{exc} to
generate the excitation current control signal. Such
amplitude control circuits are also familiar to those
skilled in the art. For an example of such an amplitude
control circuit, reference is again made to Corolis mass
flowmeters of the "PROMASS I" series. The amplitude
control circuit of the latter is preferably designed so
that in the above-mentioned first, flexural mode, the
vibrations of the respective flow tube are maintained at
a constant, i.e., density-independent, amplitude value.

The method of determining a viscosity η of the fluid in
accordance with the invention will now be explained in
more detail as applied to the above-described transducer
assembly 10. It should be noted that by the term
"viscosity", both a dynamic viscosity and a kinematic
viscosity of the fluid can be understood, since the two
viscosities can be readily converted into one another via
the density of the fluid, which is also measured during
operation of the vibration meter. Furthermore, instead of
the viscosity η, its reciprocal, i.e., a fluidity of the
fluid, can be determined.

In vibration meters with at least one flow tube
oscillating in the predetermined manner, the spatial
deflections of the respective flow tube cause motions of

the fluid, which produce shear forces. These shear forces
in the fluid are also determined by the viscosity η of
the fluid and, in the form of friction losses, have a
damping effect on the oscillating flow tube.

5

It has turned out that a ratio i_{exc}/θ of the excitation
current i_{exc} to a velocity θ of a shear-forces-inducing
motion of the fluid, which velocity is not directly
measurable, is a representative estimate of a damping

10   that counteracts this deflection. This damping of the
deflection is also determined by a damping component that
is due to viscous friction within the fluid, and can thus
serve to determine viscosity. Accordingly, to determine
the viscosity η, the velocity θ of the aforementioned

15   motions of the fluid is determined in addition to the
excitation current i_{exc}.

For the viscosity-measuring method described in the
above-mentioned U.S. Patent 4,524,610, the velocity θ is

20   estimated of a driving motion performed by a driving
lever ("yoke"), which driving motion induces torsion in a
corresponding flow tube. This driving lever thus
corresponds approximately to lever arrangement 15.

25   However, lever arrangement 15 is only conditionally
suited for measuring the velocity θ to determine the
viscosity of a fluid by a transducer assembly of the kind
described; on the one hand, because the position of the
axis of rotation of lever arrangement 15, as mentioned,

30   is variable and may therefore be determined on a
continuous basis, and, on the other hand, because such a
lever arrangement is frequently not provided on
transducer assemblies of the kind described, particularly
in Coriolis mass flow/density meters.

35

Therefore, according to the fundamental idea of the
invention, the velocity θ is not sensed directly at lever
arrangement 15 of transducer assembly 10, but is derived
from the sensor signals x_{s1}, x_{x2} provided by sensor
5   arrangement 60.

The use of the sensor signals x_{s1}, x_{x2} for measuring the
viscosity η is based on the surprising recognition that
the velocity θ of the motion of the fluid, which causes
10   the viscous friction, has, at least in the operating
range of transducer assemblies of the kind described, a
reproducible relationship, particularly a linear
relationship, to the instantaneous lateral deflection of
flow tube 13. Thus, it can be assumed with a good
15   approximation that

$$X_{\theta} = K_1 \cdot X_v \qquad\qquad (1)$$

where
20   X_v =   a velocity value derived from sensor signal x_{s1}
                and/or from sensor signal x_{s2} and
                representative of an instantaneous velocity of
                the lateral deflection of flow tube 13
        X_{θ} =   an estimate of the velocity θ of the motion of
25   the fluid, which causes shear forces and, thus,
                viscous friction in the fluid
        K_1 =   a proportionality factor to be determined,
                particularly by calibration measurements.

30   The velocity value X_v may be a signal value, e.g., an
instantaneous signal amplitude, derived either from a
single sensor signal x_{s1}, x_{s2} or from both sensor signals
x_{s1}, x_{s2}, particularly from the sum of the latter,
$x_{s1} + x_{s2}$. If sensors 17, 18 are arranged symmetrically
35   with respect to the midpoint of flow tube 13, and the

sensor signals x_{s1}, x_{s2}, as mentioned, have the same
amplitude or an amplitude regulated at the same value,
the signal sum $x_{s1} + x_{s2}$ in transducer assembly 10 of the
embodiment is proportional to the lateral deflection at
5   the midpoint of flow tube 13.

To generate the estimate X_θ of the velocity θ, the
evaluating circuit 50B, as shown in Figs. 5 and 6,
comprises an input stage 51 with a velocity or first
10   measuring circuit 511, which processes the sensor signal
x_{s1} and/or the sensor signal x_{s2} to generate the velocity
value X_v. Such a measuring circuit, particularly a
circuit measuring signal amplitudes, is shown, for
example, in U.S. Patent 5,648,616 or
15   European Patent 866 319, the disclosers of which are
hereby incorporated by reference.

As shown schematically in Fig. 6, this input stage 51
further comprises a multiplier 512, which serves to
20   implement Equation (1), i.e., which multiplies the
velocity value X_v, provided by measuring circuit 511 and
presented to a first input, by a velocity proportionality
factor K_1, presented to a second input, and thus produces
as output the estimate X_θ.
25

The relationship formulated by Equation (1) may be
determined for respective concrete realizations of
transducer assembly 10 by suitable calibration
measurements, and implemented in meter electronics 50. To
30   determine the proportionality factor K_1, for example, the
actual velocity of the torsion at the midpoint of flow
tube 13 may be determined during a calibration
measurement and related to the simultaneously generated
sensor signals x_{s1} and/or x_{s2}. It is also possible to
35   calculate the proportionality factor K_1 for a series of

transducers numerically, for example by using finite-element methods familiar to those skilled in the art.

Particularly if the fluid to be measured is a non-Newtonian fluid, the effect of the instantaneous mass flow rate on the velocity θ, and thus on the determination of the estimate X_θ, may be taken into account. In a non-Newtonian fluid, the shear forces would decrease with increasing mass flow rate m.

To calibrate the transducer assembly 10, two or more different fluids with known parameters, such as density ρ, mass flow rate m, viscosity η, and/or temperature, are passed one after the other through transducer assembly 10, and the responses of transducer assembly 10, such as the instantaneous excitation current i_{exc} and/or the instantaneous excitation frequency f_{exc}, are measured. The set parameters and the respective measured responses of transducer assembly 10 are related to each other, and thus mapped onto the corresponding calibration constants, such as the proportionality factor K_1. The calibration constants determined can then be stored in the form of digital data in a table memory of evaluating circuit 50B; however, they can also be used as analog settings for suitable arithmetic circuits. At this point it should be noted that the calibration of transducers is familiar to those skilled in the art and therefore need not be explained in greater detail.

The damping of the vibrations of flow tube 13, besides being determined by the damping component due to viscous friction, is also determined by a damping component that is virtually independent of the fluid. This damping component is caused by friction forces that act in excitation arrangement 16 and in the material of flow tube 13, for example. In other words, the measured

excitation current i_{exc} represents the entirety of the friction forces and/or friction torques in transducer assembly 10. Accordingly, to determine the viscosity η of the fluid, the fluid-independent damping component may be

5   eliminated from the ratio i_{exc}/θ, i.e., a ratio $\Delta i_{exc}/\theta$ of an excitation current component Δi_{exc}, which corresponds to the damping component of the excitation current i_{exc} that is due to viscous friction, to the velocity θ may be determined.

10

To obtain a friction value $X_{\Delta i}$ representative of the excitation current component Δi_{exc} and thus of the viscous friction, during operation of the vibration meter, a no-load-current value K_{i0}, which represents the

15   aforementioned friction forces in excitation arrangement 16, is subtracted in input stage 51 from the excitation current i_{exc} or from a measured value representing the instantaneous excitation current. To accomplish this, input stage 51, as shown schematically in Fig. 6,

20   comprises a second measuring circuit 513, particularly a digitizing measuring circuit, which subtracts the no-load current value K_{i0} applied at a subtrahend input from the excitation current i_{exc} or the measured excitation current value applied at a minuend input and thus produces as

25   output the friction value $X_{\Delta i}$.

The no-load current value K_{i0}, too, may be determined during a calibration of the vibration meter, e.g. for an evacuated or only air-conducting flow tube 13, and stored

30   or set in meter electronics 50. It is readily apparent to those skilled in the art that if necessary, other physical parameters influencing the no-load current value K_{i0}, such as an instantaneous temperature of the flow tube and/or the fluid, may be taken into account in

35   calibrating the no-load current value K_{i0}.

To generate a corresponding quotient value $X_{\Delta i}/X_\theta$ for the damping component $\Delta i_{exc}/\theta$, which is due to viscous friction in the fluid, evaluating circuit 50B, as shown in Fig. 5, further comprises a first function block 52, which serves to divide the measured friction value $X_{\Delta i}$, applied at a dividend input, by the estimate X_θ, applied at a divisor input.

In determining the viscosity η by a transducer assembly of the kind described, besides the excitation current i_{exc} and the velocity θ, a frequency of the vibrations of flow tube 13 as well as the density ρ of the fluid may be taken into account, cf. U.S. Patent 4,524,610.

To that end, the evaluating circuit 50B further comprises a correction evaluating or second function block 53, which serves to derive from the measured density value X_ρ and the measured excitation frequency value X_ρ a corresponding correction value $X_{\rho,f}$, which is dependent on the density ρ of the fluid and on the excitation frequency f_{exc}.

Both the density value X_ρ and the excitation frequency value X_f are values which are commonly measured during operation of vibration meters of the kind described, particularly of Coriolis mass flowmeter-densimeters, cf., for example, U.S. Patent 4,187,721, 4,524,610, 4,876,879, 5,648,616, or 5,687,100, or European Patent 866 319, the disclosers of which are hereby incorporated by reference. Thus it can be assumed that these measured values X_f, X_ρ are available for determining the viscosity η in accordance with the invention.

For the correction value $X_{\rho,f}$, particularly with flow tube
13 torsionally vibrating in the manner described, the
following relationship, which is implemented with
function block 53, is true with a good approximation:

5

$$X_{\rho,f} = X_\rho \cdot X_f \qquad (2)$$

If displacement sensors are used for sensors 17, 18,
instead of the simple excitation frequency value X_f, the
10   square X_f^2 of this value is used to determine the
correction value $X_{\rho,f}$, i.e., besides a multiplier for
Equation (2), function block 53 may contain a further
multiplier or a squarer.

15   As shown in Fig. 5, both the quotient value $X_{\Delta i}/X_\theta$ and the
correction value $X_{\rho,f}$ are supplied to a viscosity or third
function block 54 of evaluating circuit 50B, which
derives the viscosity value X_η from these values.

20   In a preferred embodiment of the invention, the
determination of the viscosity η is based on the
following relationship:

$$X_\eta = \frac{K_2}{X_{\rho,f}} \cdot \left(\frac{X_{\Delta i}}{X_\theta} \right)^2 \qquad (3)$$

25

where K_2 is a constant to be determined by calibration,
particularly a constant dependent on the square of the
nominal diameter of flow tube 13.

30   It has turned out that the lower the viscosity η and/or
the higher the density ρ of the fluid, the more closely
the viscosity value X_η determined according to Eq. (3)
will conform to the actual viscosity η. Furthermore, the

greater the nominal diameter of flow tube 13, the more accurately the viscosity η will be determined in this embodiment of the invention.

Therefore, in a further preferred embodiment of the method of the invention, a more accurate determination of the viscosity value X_η, particularly at a viscosity η greater than 5 Pas (= pascal seconds) and/or at nominal flow tube diameters less than 8 mm (= millimeters), is based on the following relationship:

$$X_\eta = \frac{1}{2} \cdot K_2 \cdot K_3 \cdot K_4 \cdot X_{\rho,f} \cdot \left(1 - \sqrt{1 - \frac{K_4}{K_3 \cdot X_{\rho,f}} \cdot \frac{X_{\Delta i}}{X_\theta}}\right)^2 \quad (4)$$

where
  K_3 =   a calculated constant and
  K_4 =   a constant to be determined by calibration.

Equation (4) represents a universal solution for transducers whose flow tube or flow tubes are excited into torsional vibrations about a longitudinal flow tube axis. For the transducer assembly 10 of the embodiment, a value of constant K_3 lies in a range of about 0.24 to 0.25, for example. Equation (4) takes account of the fact that within the operating range of transducers of the kind described, particularly of transducers with a flow tube performing torsional vibrations as described, the effect of the viscosity-dependent friction forces acting in the fluid on the excitation current component Δi_{exc} decreases in a radial direction toward the longitudinal flow tube axis. The constant K_3 is a coefficient for a quadratic part of the aforementioned decrease. If the excitation current component Δi_{exc}, and thus the friction value $X_{\Delta i}$, tends to very small values, Equation (4) will change to Equation (3).

To implement Equations (3) and (4), function block 54, in
preferred embodiments of the invention shown in Figs. 7
and 8, respectively, comprises a divider 541 with a

5   dividend input for the quotient value $X_{\Delta i}/X_{\theta}$ and a divisor
input for the correction value $X_{\rho,f}$ to produce a first
intermediate value. Function block 54 further comprises
an arithmetic stage 542 with a first input for the first
intermediate value to produce a second intermediate value

10   proportional to the viscosity η, and a multiplier 543,
which multiplies the second intermediate value by the
constant K_2 to obtain the viscosity value X_{η}.

To implement Equation (3), arithmetic stage 542, in

15   another preferred embodiment of the invention, is
configured as a multiplier which, as shown schematically
in Fig. 7, serves to multiply the first intermediate
value, provided by divider 541, by the quotient value
$X_{\Delta i}/X_{\theta}$ to produce the second intermediate value.

20
To implement Equation (4), arithmetic stage 542, in a
further preferred embodiment of the invention, comprises
a square-root extractor for the difference under the
radical sign of Equation (4) and a squarer for the

25   difference with the radical sign. Arithmetic stage 542
further serves to multiply a square value generated by
the squarer by the constants K_3 and K_4 and by the
correction value $X_{\rho,f}$ to produce the second intermediate
value.

30
It has also turned out that the above-described estimate
of the velocity θ according to Eq. (1) also depends to a
slight degree on the density ρ of the fluid, so that

35                              $$K_1 = K_1(\rho) \qquad\qquad (5)$$

Investigations have shown that for the transducer
assembly 10 of the embodiment, the proportionality factor
K_1, taking account of its density dependence, may be
5   determined from:

$$K_1 = \frac{K_{1,0}}{1 + K_5 \cdot \left(X_\rho - \rho_0 \right)} \qquad (6)$$

where
10   ρ_0 =   a set or measured density of a calibration
                fluid serving to calibrate transducer
                assembly 10;

        $K_{1,0}$ =   a proportionality factor for the transducer
15   assembly 10 conducting the calibration fluid;
                and

        K_5 =   a constant to be calibrated, which is dependent
                on the nominal diameter of flow tube 13.

20

In analogy to Eq. (1), the proportionality factor $K_{1,0}$ is
given by

$$K_{1,0} = \frac{X_{\theta,0}}{X_{v,0}} \qquad (7)$$

25

where
        $X_{\theta,0}$ =   a first measured calibration value,
                representative of the velocity θ for the flow
                tube 13 conducting the calibration fluid; and

30

        $X_{v,0}$ =   a second measured calibration value, derived
                from sensor signal x_{s1} and/or sensor signal x_{s2}
                and representative of a velocity of the lateral

deflection of the flow tube 13 conducting the
calibration fluid.

5   Equation (6), as shown schematically in Fig. 9, is
implemented with a proportionality factor function block
514 of input stage 51.

The aforementioned function blocks 52, 53, 54, 514 and
the multiplier 512,which serve to produce the viscosity
10   value X_η, may be implemented in the manner familiar to
those skilled in the art using, for instance, a
microcomputer provided in evaluating circuit 50B and
suitable program codes that are implemented and executed
in this microcomputer. The implementation of the above
15   Equations (1), (2), (3), (4), and (6) in the respective
function blocks as well as the creation of microcomputer
program codes serving to implement Equations (1), (2),
(3), (4), and (6) are familiar to those skilled in the
art and can thus be carried out without more detailed
20   explanations. Of course, the equations can also be
represented, in whole or in part, using suitable
discrete-component, analog and/or arithmetic circuits in
evaluating circuit 50B. In a corresponding manner, input
stage 51 can be implemented with the aforementioned
25   microcomputer, in which case the sensor signals x_{s1}, x_{s2}
and the sensed excitation current i_{exc} may, of course, be
converted into corresponding digital signals using
analog-to-digital converters, cf. particularly
European Patent 866 319.
30
In the transducer assembly 10 of the embodiment, because
of the torsion in particular, a ratio $\Delta i_{exc}/i_{exc}$ of the
excitation current component Δi_{exc} to the excitation
current i_{exc}, normalized to a reference viscosity of about
35   4 Pas, can be up to 90%, i.e., transducer assembly 10
exhibits a very high sensitivity to the viscosity η.

It is also possible to use other transducers familiar to those skilled in the art, such as transducers with a helically bent flow tube, as are described, for example, in U.S. Patent 5,357,811, or 5,557,973 for measuring the viscosity η. Also, as mentioned above, transducers with straight or bent flow tubes as are described, for example, in U.S. Patent 5,301,557, 5,648,616 or 5,796,011, can be used for measuring the viscosity η. Such transducers may, for instance, have a ratio $\Delta i_{exc}/i_{exc}$, related to the aforementioned reference viscosity, of approximately 70% to 80%.

While the invention has been illustrated and described in detail in the drawings and forgoing description, such illustration and description is to be considered as exemplary not restrictive in character, it being understood that only exemplary embodiments have been shown and described and that all changes and modifications that come within the spirit and scope of the invention as described herein are desired to protected.